



# Internet Office 120V 500VA 280W Standby UPS, USB port, 6 Outlets, Tel/DSL/Ethernet Protection

### MODEL NUMBER: INTERNETOFFICE500





#### Description

Tripp Lite's INTERNETOFFICE500 standby UPS system offers surge suppression and long-lasting battery support for personal computers, internetworking equipment and other sensitive electronics. Internal UPS circuits support entry-level PC systems for up to 30 minutes during power failures and brownouts so that connected equipment can be shut down without data loss. Offers complete desktop power protection in an attractive gray tower configuration. Includes 3 battery-supported outlets for computer, monitor and one vital system peripheral, plus 3 additional surge suppression-only outlets for printers and other system accessories not requiring battery support. USB port enables optional unattended system shutdown without data loss in case of extended power failure; cable included. PowerAlert software available via FREE download. Built-in TEL/DSL or ethernet line surge suppression protects connected equipment from damaging surges. Built-in audible alarm and 3 front-panel LEDs indicate line power status, battery power status and battery low/replace status. 500VA/280W power handling ability supports entry-level PCs, network workstations, point-of-sale equipment, small business phone systems, audio/video equipment and home theater systems. Offers 4.6 min. battery runtime with a full load of 500VA and 14.8 min. with a half load of 250VA. Supports user battery replacement via built-in access panel. \$150,000 connected equipment insurance (USA, Puerto Rico, & Canada only).

#### **Features**

- INTERNETOFFICE500 standby UPS system offers UPS battery support, plus complete AC and tel/Ethernet modem line surge suppression
- Supports entry level PC systems for up to 30 min. during brownouts and power failures, enabling safe system shutdown
- Supports a max load of 500VA/280W for 4.6 min.
- Supports a half load of 250VA/140W for 14.8 min.
- Supplies battery-derived AC output during brownouts starting at 99V and overvoltages starting at 147V; user adjustment allows fine tuning of brownout response to any setting from 83V to 99V
- Attractive gray tower configuration
- Includes 3 battery-supported outlets, 3 surge suppression-only outlets and 6-ft. AC line cord (all NEMA 5-15)

#### **Highlights**

- 500VA tower 120V standby UPS
- Maintains AC output during power failures
- 3 UPS battery supported outlets, 3 surge-only outlets
- USB port, TEL/DSL/ethernet protection
- NEMA 5-15P input plug and 6 NEMA 5-15R outlets

#### **Package Includes**

- INTERNETOFFICE500 UPS
   System
- USB cable
- Phone cable
- Instruction manual





- USB port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from tripplite.eaton.com/products/power-alert
- HID-compliant USB port also enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- Supports Tripp Lite's WatchDog software application to restore unresponsive programs by automatically
  restarting them and rebooting completely locked computers by automatically switching UPS power off
  and back on again
- Dataline suppression jacks protect a single dialup phone/DSL line or network Ethernet line connection
- Audible alarm and 3 front-panel LEDs indicate line power, battery power and battery low/replace status
- 500VA/280W power handling ability supports a variety of computer, internetworking, telecom and consumer electronics equipment
- Supports user battery replacement via built-in access panel
- Optional PDUB15 bypass PDU enables hot-swappable UPS replacement with no disruption to connected equipment
- Compatible with 120V/60Hz applications for USA, Canada, Mexico and more
- \$150,000connected equipment insurance (USA, Puerto Rico, & Canada only)

## **Specifications**

| OVERVIEW  |                                     |  |
|---|-------------------------------------|--|
| UPC Code  | 037332032706                        |  |
| UPS Type  | Standby                             |  |
| INPUT   |                                     |  |
| Input Phase                                     | Single-Phase                        |  |
| Rated input current (Maximum Load)              | 10A                                 |  |
| Nominal Input Voltage(s) Supported              | 120V AC                             |  |
| UPS Input Connection Type                       | 5-15P; Right-Angled                 |  |
| UPS Input Cord Length (ft.)                     | 6                                   |  |
| UPS Input Cord Length (m)                       | 1.8                                 |  |
| Recommended Electrical Service                  | 15A 120V                            |  |
| OUTPUT  |                                     |  |
| Output Capacity (VA)                            | 500                                 |  |
| Output Capacity (Watts)                         | 280                                 |  |
| Nominal Voltage Details                         | 115v nominal output in battery mode |  |
| Frequency Compatibility                         | 60 Hz                               |  |
| Output Voltage Regulation (Battery Mode)        | +/- 5%                              |  |
| UPS Output Receptacles (Surge Suppression Only) | 3 UPS outlets, 3 surge-only outlets |  |
| Hot-Swap PDU options                            | PDUB15 (2U / 8 5-15R outlets)       |  |
| Output AC Waveform (AC Mode)                    | Sine wave                           |  |





| Output AC Waveform (Battery Mode)                             | PWM sine wave   |  |
|---|---|--|
| Nominal Output Voltage(s)<br>Supported                        | 110V; 115V; 120V  |  |
| Output Receptacles  | (6) 5-15R   |  |
| Individually Controllable Load Banks                          | No  |  |
| BATTERY   |   |  |
| Runtime Full Load (min.)                                      | 4.6 min. (280w)   |  |
| Runtime Half Load (min.)                                      | 14.8 min. (140w)  |  |
| Expandable Runtime  | No  |  |
| DC System Voltage (VDC)                                       | 12  |  |
| Battery Access  | Battery access door   |  |
| Internal UPS Replacement Battery<br>Cartridge                 | <a class="productLink" href="//tripplite.eaton.com/UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-&lt;br&gt;Belkin-Best-Powerware-Liebert-other-UPS~RBC51">RBC51</a>      |  |
| Battery Replacement Description                               | Hot-swappable, user replaceable batteries   |  |
| USER INTERFACE, ALERTS & CONTROLS                             |   |  |
| Switches  | 2 Switches control off/on power status and alarm-cancel/self-test operation   |  |
| Alarm Cancel Operation  | Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-<br>battery status   |  |
| Audible Alarm   | Audible alarm indicates power-failure and low-battery conditions  |  |
| LED Indicators  | 3 LEDs indicate line power, battery power and battery low/replace status  |  |
| SURGE / NOISE SUPPRESSION                                     |   |  |
| UPS AC Suppression Joule Rating                               | 480   |  |
| UPS AC Suppression Response<br>Time                           | Instantaneous   |  |
| UPS Dataline Suppression                                      | 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet  |  |
| EMI / RFI AC Noise Suppression                                | Yes   |  |
| AC Suppression Joule Rating                                   | 480   |  |
| AC Suppression Response Time                                  | Instantaneous   |  |
| PHYSICAL  |   |  |
| Primary Form Factor   | Tower   |  |
| Installation Form Factors Supported with Included Accessories | Tower   |  |
| Installation Form Factors Supported with Optional Accessories | Wallmount ( <a class="productLink" href="//tripplite.eaton.com/Wall-Mount-Bracket-Installation-Accessories-&lt;br&gt;for-UPS-Systems~UPSWM">UPSWM</a> - tower mounting kit) |  |
| Primary UPS Depth (mm)  | 178   |  |
| Primary UPS Height (mm)                                       | 216   |  |
|   |   |  |





| Primary UPS Width (mm)   | 132   |
|--|---|
| Shipping Dimensions (hwd / in.)  | 9.25 x 8.10 x 11.90   |
| Shipping Dimensions (hwd / cm)   | 23.50 x 20.57 x 30.23   |
| Shipping Weight (lbs.)   | 13.40   |
| Shipping Weight (kg)   | 6.08  |
| UPS Housing Material   | PVC   |
| UPS Power Module Dimensions<br>(hwd, cm)   | 21.59 x 13.21 x 17.78   |
| UPS Power Module Dimensions (hwd, in.)   | 8.5 x 5.2 x 7   |
| UPS Power Module Weight (kg)   | 6.35  |
| UPS Power Module Weight (lbs.)   | 14  |
|  |   |
| ENVIRONMENTAL  |   |
| Operating Temperature Range  | +32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius   |
| Storage Temperature Range  | +5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius  |
| Relative Humidity  | 0 to 95%, non-condensing  |
| AC Mode BTU / Hr. (Full Load)  | 68  |
| AC Mode Efficiency Rating (100% Load)  | 94%   |
| COMMUNICATIONS   |   |
| PowerAlert Software  | For local monitoring via the UPS's built-in USB port, download PowerAlert software at   |
|  | https://tripplite.eaton.com/products/power-alert  |
| Communications Cable   | https://tripplite.eaton.com/products/power-alert         USB interface cable included   |
| Communications Cable<br>WatchDog Compatibility   | https://tripplite.eaton.com/products/power-alert  |
|  | https://tripplite.eaton.com/products/power-alert         USB interface cable included   |
| WatchDog Compatibility<br>Network UPS Tools (NUT)  | https://tripplite.eaton.com/products/power-alert         USB interface cable included         Supports Watchdog application, OS and hard-reboot restart options for remote applications         NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at   |
| WatchDog Compatibility<br>Network UPS Tools (NUT)<br>Compatibility   | https://tripplite.eaton.com/products/power-alert         USB interface cable included         Supports Watchdog application, OS and hard-reboot restart options for remote applications         NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite   |
| WatchDog Compatibility<br>Network UPS Tools (NUT)<br>Compatibility<br>Communications Interface   | https://tripplite.eaton.com/products/power-alert         USB interface cable included         Supports Watchdog application, OS and hard-reboot restart options for remote applications         NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite   |
| WatchDog Compatibility Network UPS Tools (NUT) Compatibility Communications Interface LINE / BATTERY TRANSFER  | https://tripplite.eaton.com/products/power-alert         USB interface cable included         Supports Watchdog application, OS and hard-reboot restart options for remote applications         NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite         USB (HID enabled)   |
| WatchDog Compatibility Network UPS Tools (NUT) Compatibility Communications Interface LINE / BATTERY TRANSFER Transfer Time Low Voltage Transfer to Battery  | https://tripplite.eaton.com/products/power-alert         USB interface cable included         Supports Watchdog application, OS and hard-reboot restart options for remote applications         NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite         USB (HID enabled)         2-4 milliseconds  |
| WatchDog Compatibility Network UPS Tools (NUT) Compatibility Communications Interface LINE / BATTERY TRANSFER Transfer Time Low Voltage Transfer to Battery Power (Setpoint) High Voltage Transfer to Battery  | https://tripplite.eaton.com/products/power-alert         USB interface cable included         Supports Watchdog application, OS and hard-reboot restart options for remote applications         NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite         USB (HID enabled)         2-4 milliseconds         99V (adjustable to 83V via potentiometer)  |
| WatchDog Compatibility         Network UPS Tools (NUT)         Compatibility         Communications Interface         LINE / BATTERY TRANSFER         Transfer Time         Low Voltage Transfer to Battery         Power (Setpoint)         High Voltage Transfer to Battery         Power (Setpoint)   | https://tripplite.eaton.com/products/power-alert         USB interface cable included         Supports Watchdog application, OS and hard-reboot restart options for remote applications         NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite         USB (HID enabled)         2-4 milliseconds         99V (adjustable to 83V via potentiometer)  |
| WatchDog Compatibility         Network UPS Tools (NUT)         Compatibility         Communications Interface         LINE / BATTERY TRANSFER         Transfer Time         Low Voltage Transfer to Battery         Power (Setpoint)         High Voltage Transfer to Battery         Power (Setpoint)         FEATURES & SPECIFICATIONS         Cold Start (Startup in Battery Mode                                 | https://tripplite.eaton.com/products/power-alert         USB interface cable included         Supports Watchdog application, OS and hard-reboot restart options for remote applications         NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite         USB (HID enabled)         2-4 milliseconds         99V (adjustable to 83V via potentiometer)         176 (adjustable to 147 via potentiometer)  |
| WatchDog Compatibility         Network UPS Tools (NUT)         Compatibility         Communications Interface         LINE / BATTERY TRANSFER         Transfer Time         Low Voltage Transfer to Battery         Power (Setpoint)         High Voltage Transfer to Battery         Power (Setpoint)         FEATURES & SPECIFICATIONS         Cold Start (Startup in Battery Mode         During a Power Failure) | https://tripplite.eaton.com/products/power-alert         USB interface cable included         Supports Watchdog application, OS and hard-reboot restart options for remote applications         NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite         USB (HID enabled)         2-4 milliseconds         99V (adjustable to 83V via potentiometer)         176 (adjustable to 147 via potentiometer)         Cold-start operation supported |





| APPLICATIONS  |  |
|---|--|
| UPS Applications  | Computer/Peripherals   |
| WARRANTY & SUPPORT  |  |
| Product Warranty Period (U.S. & Canada)                       | 3-year limited warranty  |
| Product Warranty Period (Latin<br>America)                    | 3-year limited warranty  |
| Product Warranty Period<br>(International)                    | 2-year limited warranty  |
| Product Warranty Period (Mexico)                              | 3-year limited warranty  |
| Connected Equipment Insurance<br>(U.S., Canada & Puerto Rico) | \$150,000 <a class="insuranceLink" href="//tripplite.eaton.com/support/insurance-policy">Ultimate Lifetime Insurance</a> |

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com

Г

© 2024 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.