



OmniSmart 1500VA 2U Rack/Tower Line-Interactive 120V UPS with LCD display and USB port

MODEL NUMBER: OMNI1500LCD











Highlights

- 1500VA / 1.5kVA 2U rack/tower 120V line interactive UPS with LCD display
- Corrects brownouts and overvoltages from 75V to 147V
- LCD screen reports input voltage, battery charge and UPS status
- USB, TEL/DSL/ethernet protection, Surge-only outlets, Rackmount kit
- NEMA 5-15P input plug and 8 NEMA 5-15R outlets

Package Includes

- OMNI1500LCD UPS System
- USB Cable
- Phone Cable
- Rackmount brackets
- Instruction manual

Description

Tripp Lite's OMNI1500LCD Line-Interactive Digital UPS System offers voltage regulation, surge suppression and long-lasting battery support for personal computers, and small business network applications. Automatic Voltage Regulation (AVR) circuits regulate brownouts and overvoltages from 75V to 147V back to usable levels without using battery power. Offers complete power protection with support for upright tower 2U rackmount installation in an attractive all-black cabinet design. Includes 6 batterysupported outlets plus 2 additional surge suppression only outlets for devices not requiring battery support. Built-in USB port enables optional unattended system shutdown without data loss in case of extended power failure; cable included. PowerAlert software available via free download from www.tripplite.eaton.com. HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Built-in single-line RJ-45 jacks offer protection for equipment with single-line tel/DSL or network Ethernet connection. Built-in audible alarm and large LCD front panel voltage display indicates line power status, battery power status, battery low/replace status and voltage regulation operation. The LCD display includes a dimmer switch and can be rotated for easy viewing in horizontal or vertical placement. 1500VA power-handling capacity supports entry-level PCs, home entertainment systems, network workstations and audio/video components. Offers 2.5 minutes battery runtime at full load of 1500VA and 9 minutes at 750VA. \$200,000 connected equipment insurance (USA, Puerto Rico and Canada only).

Features

- LCD Display indicates input voltage, battery capacity and a variety of operating conditions. Display is rotatable for easy viewing whether UPS is in vertical or horizontal position
- OMNI1500LCD Digital Uninterruptible Power Supply offers voltage regulation, surge suppression and long-lasting battery support during blackouts
- Regulates brownouts and overvoltages from 75V to 147V back to usable levels without using battery power
- 6 UPS battery-supported outlets for critical items, plus 2 additional surge suppression-only outlets for accessories not requiring battery support
- Included USB monitoring port and cable enables unattended shutdown in the case of extended power failure
- HID-compliant USB port enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- PowerAlert software available via free download from tripplite.eaton.com
- Set of phone/network protection jacks protects a single dialup/DSL phone line or network Ethernet





connection

- 1500VA/825W power handling ability supports a variety of electronic equipment
- 2.5 min. full load runtime (1500VA/825W); 9 min. half-load runtime (750VA/413W)
- Cabinet adapts to tower or rackmount shelf format. Rackmount installation brackets for 2U installation included
- \$200,000 connected equipment insurance (USA, Puerto Rico and Canada only).

Specifications

OVERVIEW			
UPC Code	037332155849		
UPS Type	Line-Interactive		
INPUT			
Input Phase	Single-Phase		
Rated input current (Maximum Load)	10A		
Nominal Input Voltage(s) Supported	120V AC		
UPS Input Connection Type	5-15P		
Input Circuit Breakers	10A		
UPS Input Cord Length (ft.)	6		
UPS Input Cord Length (m)	1.8		
Recommended Electrical Service	15A 120V		
ОИТРИТ	OUTPUT		
Output Capacity (VA)	1500		
Output Capacity (kVA)	1.5		
Output Capacity (Watts)	825		
Frequency Compatibility	60 Hz		
Output Voltage Regulation (Line Mode)	-18%, +8%		
Output Voltage Regulation (Battery Mode)	115V (+/- 5%)		
UPS Output Receptacles (Surge Suppression Only)	6 UPS outlets, 2 surge-only outlets		
Output AC Waveform (AC Mode)	Sine wave		
Output AC Waveform (Battery Mode)	PWM sine wave		
Nominal Output Voltage(s) Supported	115V; 120V		
Output Receptacles	(8) 5-15R		
Individually Controllable Load Banks	No		





Runtime Half Load (min.) Expandable Runtime No DC System Voltage (VDC) 24 Battery Recharge Rate (Included Batteries) Less than 3.5 hours from 10% to 90% VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 33 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rackflower viewing Switches 2 Switches control offion power status and alarm-cance/self-test operation; dimmer switch controls LCD brightness Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status. Audible alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators Front panel LCD display SURGE / NOISE SUppression UPS AC Suppression Joule Rating UPS AC Suppression Joule Rating Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out): 101100Base T Ethernet EMI / RFI AC Noise Suppression 1 line TEL/DSL (1 in / 1 out): 101100Base T Ethernet EMI / RFI AC Noise Suppression Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessionies Maximum Device Depth (cm) 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower			
Expandable Runtime Expandable Runtime No DC System Voltage (VDC) 24 Battery Recharge Rate (Included Batter) Battery Recharge Rate (Included Batter) Batterises) Voltage Regulation Description Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 75 and 92 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rackflower viewing Switches 2 Switches control off/on power status and alarm-cance/self-test operation; dimmer switch controls LCD brightness Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status. LED Indicators Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS Dataline Suppression Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out); 10/1008ase T Eithemet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Installation Form Factors Supported With Indicated Accessories Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported With Indicated Accessories Maximum Device Depth (cm) 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower	BATTERY		
Expandable Runtime No DC System Voltage (VDC) 24 Battery Recharge Rate (Included Batteries) 24 Batteries) 25 VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 128 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 93 and 107 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for racktrower viewing Switches 2 Switches control offion power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status LED Indicators Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Installation Suppression Installation Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Installation Form Factors Supported With Included Mounting Accessory Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported With Included Accessories Maximum Device Depth (cm) 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm)	Runtime Full Load (min.)	2.5 min. (825w)	
DC System Voltage (VDC) 24 Battery Recharge Rate (Included Batteries) 24 Battery Recharge Rate (Included Batteries) 24 VOLTAGE REGULATION VOLTAGE REGULATION VOITAGE REGULATION VOITAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147 Voltage Regulation Description Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status. LCD screen rotates for rack/tower viewing Switches 2 switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status. Audible Alarm Audible alarm indicates power-failure and low-battery conditions Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 420 UPS AC Suppression Suppression Instantaneous Instantaneous Instantaneous PAYSICAL PHYSICAL PHYSICAL PHYSICAL PHYSICAL PHYSICAL PHYSICAL PHYSICAL PAGE A Rackmount Rack Height 2U Cooling Method Fan Installation Form Factor Supported with included Mounting Accessory Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with included Accessories Maximum Device Depth (cm) 26.657	Runtime Half Load (min.)	9 min. (413w)	
Battery Recharge Rate (Included Batteries) Voltage Regulation Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 193 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen indicates input voltage, 5-bar battery status, and screen indicates input voltage, 5-bar battery status, and screen indicates input voltage, 5-bar battery status, and screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery screen indicate	Expandable Runtime	No	
VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 128 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status. LCD screen rotates for rackforwer viewing Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness bettery status. Audible alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status. LED Indicators Front panel LCD display SURGE / Noise Suppression UPS AC Suppression Joule Rating UPS AC Suppression Joule Rating UPS AC Suppression Tesponse Instantaneous UPS Dataline Suppression Pesponse Instantaneous 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported With included Accessories Maximum Device Depth (cm) 26.67	DC System Voltage (VDC)	24	
Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 93 and 107 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overfoad, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing Switches 2 switches control off/or power status and alarm-cancel/self-test operation, dimmer switch controls LCD brightness Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Pear of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories Maximum Device Depth (cm) 2 56.67	Battery Recharge Rate (Included Batteries)	Less than 3.5 hours from 10% to 90%	
Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 420 UPS AC Suppression Response Instantaneous Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories Maximum Device Depth (cm) 26.67	VOLTAGE REGULATION		
Undervoltage Correction Input voltages between 93 and 107 are boosted by 14% Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for racknower viewing Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 420 UPS AC Suppression Response Instantaneous Instantaneous UPS Dataline Suppression 1 I line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Pescription Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories Maximum Device Depth (cm) 26.67	Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147	
Severe Undervoltage Correction Input voltages between 75 and 92 are boosted by 30% USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 420 UPS AC Suppression Response Instantaneous UPS Dataline Suppression Power-fail in FEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with included Accessories Maximum Device Depth (cm) 26.67	Overvoltage Correction	Input voltages between 128 and 147 are reduced by 12%	
USER INTERFACE, ALERTS & CONTROLS Front Panel LCD Display Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overfoad, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions EED Indicators Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 420 UPS AC Suppression Response Instantaneous 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with included Accessories Maximum Device Depth (cm) 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm)	Undervoltage Correction	Input voltages between 93 and 107 are boosted by 14%	
Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with included Accessories Maximum Device Depth (cm) 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm)	Severe Undervoltage Correction	Input voltages between 75 and 92 are boosted by 30%	
Switches 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 420 UPS AC Suppression Response Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with included Accessories Maximum Device Depth (cm) 26.67	USER INTERFACE, ALERTS & CONTROLS		
Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure and low-battery conditions ED Indicators Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 420 UPS AC Suppression Response Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with included Accessories Maximum Device Depth (cm) 26.67	Front Panel LCD Display	Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing	
Audible Alarm Audible alarm indicates power-failure and low-battery conditions LED Indicators Front panel LCD display SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 420 UPS AC Suppression Response Instantaneous Time Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories 4 Maximum Device Depth (cm) 26.67	Switches	2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness	
SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating	Alarm Cancel Operation	Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status	
SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating	Audible Alarm	Audible alarm indicates power-failure and low-battery conditions	
UPS AC Suppression Joule Rating UPS AC Suppression Response Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories Maximum Device Depth (cm) 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower	LED Indicators	Front panel LCD display	
UPS AC Suppression Response UPS Dataline Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories Maximum Device Depth (cm) 26.67	SURGE / NOISE SUPPRESSION		
Time Installation Suppression 1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet EMI / RFI AC Noise Suppression Yes PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm) 26.67	UPS AC Suppression Joule Rating	420	
PHYSICAL Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm) 26.67	UPS AC Suppression Response Time	Instantaneous	
Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm) 26.67	UPS Dataline Suppression	1 line TEL/DSL (1 in / 1 out); 10/100Base T Ethernet	
Primary Form Factor Rackmount Rack Height 2U Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm) 26.67	EMI / RFI AC Noise Suppression	Yes	
Rack Height 2U Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm) 26.67	PHYSICAL		
Cooling Method Fan Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm) 26.67	Primary Form Factor	Rackmount	
Included Mounting Accessory Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm) 26.67	Rack Height	2U	
Description Pair of mounting ears enable tower and 2-4 post rackmount installation Installation Form Factors Supported with Included Accessories 2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower Maximum Device Depth (cm) 26.67	Cooling Method	Fan	
with Included Accessories 2 post 19 incl Tackflourit, 4 post 19 incl Tackflourit, 10wer Maximum Device Depth (cm) 26.67	Included Mounting Accessory Description	Pair of mounting ears enable tower and 2-4 post rackmount installation	
	Installation Form Factors Supported with Included Accessories	2 post 19 inch rackmount; 4 post 19 inch rackmount; Tower	
Maximum Device Depth (in.) 10.5	Maximum Device Depth (cm)	26.67	
	Maximum Device Depth (in.)	10.5	





Maximum Device Depth (mm)	267		
Primary UPS Depth (mm)	267		
Primary UPS Height (mm)	89		
Primary UPS Width (mm)	437		
Shipping Dimensions (hwd / in.)	7.50 x 21.50 x 15.00		
Shipping Dimensions (hwd / cm)	19.05 x 54.61 x 38.10		
Shipping Weight (lbs.)	33.40		
Shipping Weight (kg)	15.15		
UPS Housing Material	ABS		
UPS Power Module Dimensions (hwd, cm)	8.89 x 43.69 x 26.67		
UPS Power Module Dimensions (hwd, in.)	3.5 x 17.2 x 10.5		
UPS Power Module Weight (kg)	13.34		
UPS Power Module Weight (lbs.)	29.4		
Unit Dimensions (hwd / in.)	3.500 x 17.250 x 10.500		
ENVIRONMENTAL			
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius		
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius		
Relative Humidity	0 to 95%, non-condensing		
AC Mode BTU / Hr. (Full Load)	140		
AC Mode Efficiency Rating (100% Load)	95%		
COMMUNICATIONS			
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions		
PowerAlert Software	Free download from https://tripplite.eaton.com/products/power-alert		
Communications Cable	USB cable included		
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications		
Communications Interface	USB (HID enabled)		
LINE / BATTERY TRANSFER			
Transfer Time	4 milliseconds		
Low Voltage Transfer to Battery Power (Setpoint)	75		
High Voltage Transfer to Battery Power (Setpoint)	147		
FEATURES & SPECIFICATIONS	FEATURES & SPECIFICATIONS		





Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS
APPLICATIONS	
UPS Applications	Home/Office Desktop; Audio/Video
STANDARDS & COMPLIANCE	
Product Certifications	NOM (Mexico); UL 1778
Product Compliance	FCC Part 15 Class B (USA); FCC Part 68; RoHS
WARRANTY & SUPPORT	
Product Warranty Period (U.S. & Canada)	3-year limited warranty
Product Warranty Period (International)	2-year limited warranty
Product Warranty Period (Mexico)	3-year limited warranty
Product Warranty Period (Puerto Rico)	3-year limited warranty
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$200,000 Ultimate Lifetime Insurance

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2024 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.