



SmartOnline 1500VA 1350W 120V Double-Conversion Sine Wave UPS - 8 Outlets, Extended Run, Network Card Option, LCD, USB, DB9, 2U Rack/Tower, TAA

MODEL NUMBER: SU1500RTXLCD2UTAA











Provides battery backup, power protection and sine wave output for mission-critical IT installations and other network applications requiring TAA compliance.

Features

1.5kVA 1.35kW 120V Battery Backup Protects Equipment against Damage, Downtime and Data Loss

This on-line double-conversion UPS system maintains perfect output by converting AC input to DC, then reconverting UPS output to fully regulated sine wave AC. Constant on-line operation completely isolates sensitive equipment from every power problem on the AC line. The SmartOnline® SU1500RTXLCD2UTAA provides the highest level of power protection and battery backup for education, healthcare, military, government and other mission-critical IT applications where space is limited, but premium power reliability is essential.

Reliable, Expandable Battery Backup Keeps You Operational Through Power Outages

The field-replaceable, hot-swappable VRLA battery modules allow you to work through short power failures and give you enough time to safely save files and shut down your system in the case of a prolonged blackout. Zero transfer time between on-line and battery modes maintains continuous operation of connected equipment without interruption or rebooting. Extra runtime is available by connecting up to four optional extended battery modules (BP48RT2UTAA, sold separately).

Optional Network Management Card Allows Remote Access 24/7

The WEBCARDLXE network interface (sold separately) enables full remote configuration and management, including load shedding, reboots of connected equipment and safe shutdowns. The IP-based Auto Probe feature ensures continuous network uptime by communicating with other network devices, detecting lost connectivity and automatically rebooting IT equipment. Optional EnviroSense2 modules (E2MT, E2MTDO and E2MTHDI, all sold separately) provide a variety of environmental monitoring and control options. *Note: The SU1500RTXLCD2UTAA is not compatible with WEBCARDLX*.

NEMA 5-15R Outlets Protect Your Connected Components

Eight managed 5-15R outlets provide connected equipment with pure sine wave AC output and allow you to manage power consumption down to the outlet group level. Power provided by these outlets is filtered to protect connected equipment against damaging surges and line noise. Four outlets are split evenly into two programmable load banks that let you shed non-critical loads in order to extend runtime for critical loads during an outage. A cooling fan helps protect equipment from overheating.

Highlights

- Offers network-grade protection against power failures and voltage fluctuations
- Zero transfer time between online and battery modes for uninterrupted operation
- Keeps equipment running during outages to allow time for file saves and safe shutdown
- Optional WEBCARDLXE network interface enables 24/7 complete and remote control
- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases

Package Includes

- 1500VA 1350W 120V Double-Conversion UPS
- USB cable
- DB9 cable
- Rack-mounting hardware
- Tower support stands
- Safety instructions
- Quick Start Guide





Premium Protection from EMI/RFI Line Noise Helps Your Equipment Perform Better

This UPS system filters out disruptive electromagnetic and radio frequency interference that can inflict hardware damage or data loss. This EMI/RFI filtering also helps your connected components perform better and last longer.

Intuitive Front-Panel Interface for Convenient UPS Operation and Monitoring

The two-line front-panel LCD features 10 selectable screens that allow quick access to a wide range of detailed UPS and site power information. LEDs show UPS status: a green light means utility power is on, an orange light means the UPS is in battery or bypass mode and a red light indicates an active alarm or fault. The control panel rotates to accommodate both rack-mount and tower configurations.

Advanced Communications Ports Allow for Automatic Saves and Shutdowns

RS-232 and USB ports connect to a device for a variety of communication options (cables are included). A dry-contact relay port can be programmed through the LCD to provide reliable communications to automation and industrial components. The RPO/ROO port permits emergency shutdown or remote restart of all connected equipment.

Automatically Turns Back On After Power Is Restored

Battery-independent restart ensures automatic UPS power-up without user interaction after lengthy power outages, even after a complete battery discharge. This can save you a costly site visit.

Versatile Installation Options

Hardware is included for mounting the UPS system in 2U of space in an EIA-standard 19-inch 4-post rack. You can also adapt it for 2-post rack mounting with the optional RK2PC (sold separately) or tower installation using the included support stands. The eight-foot power cord with NEMA 5-15P plug connects to any compatible AC outlet.

TAA-Compliant for GSA Schedule Purchases

The SU1500RTXLCD2UTAA is compliant with the Federal Trade Agreements Act (TAA), which makes it eligible for GSA (General Services Administration) Schedule and other federal procurement contracts.

Specifications

-			
OVERVIEW			
UPC Code	786689875763		
UPS Type	On-Line		
INPUT			
Input Phase	Single-Phase		
Rated input current (Maximum Load)	12.5A		
Nominal Input Voltage(s) Supported	100V AC; 110V AC; 120V AC		
Nominal Input Voltage Description	120V factory default		
UPS Input Connection Type	5-15P		
UPS Input Cord Length (ft.)	8		
UPS Input Cord Length (m)	2.4		
Recommended Electrical Service	120V		
Input Plug Type	NEMA 5-15P		
Input Cord Length (ft.)	8		
Input Cord Length (m)	2.44		





Input Current	12.5A	
Power Factor (Input)	0.99	
ОИТРИТ		
Output Capacity (VA)	1500	
Output Capacity (kVA)	1.5	
Output Capacity (Watts)	1350	
Output Capacity (kW)	1.35	
Power Factor	0.9	
Crest Factor	3:1	
Nominal Voltage Details	120V factory-default nominal voltage	
Frequency Compatibility	50 / 60 Hz	
Frequency Compatibility Details	Online Mode: Sync with line ±5% of nominal line frequency (outside this range: ±0.5% of auto-selected nominal frequency). Battery Mode: ±0.5% of auto-selected nominal frequency	
Output Voltage Regulation (Line Mode)	+/- 1%	
Output Voltage Regulation (Economy Line Mode)	+/- 1%	
Output Voltage Regulation (Battery Mode)	+/- 2%	
Load Management Receptacles	Two switchable two-outlet load banks	
Output AC Waveform (AC Mode)	Pure Sine wave	
Output (Watts)	1350	
Output AC Waveform (Battery Mode)	Pure Sine wave	
Nominal Output Voltage(s) Supported	100V; 110V; 115V; 120V; 127V	
Output Receptacles	(8) 5-15R	
Individually Controllable Load Banks	Yes	
BATTERY		
Battery Type	Valve Regulated Lead Acid (VRLA)	
Runtime Full Load (min.)	5.8 min. (1350W)	
Runtime Half Load (min.)	16.5 min. (675W)	
Expandable Runtime	Yes	
Expandable Runtime Description	Add up to 4 extended battery modules (EBM). Part number BP48RT2UTAA .	
External Battery Pack Compatibility	BP48RT2UTAA	
DC System Voltage (VDC)	48	





Battery Recharge Rate (Included Batteries)	3 hours recharge to 90%	
Battery Access	Battery access door	
Internal UPS Replacement Battery Cartridge	744-A3297	
Battery Replacement Description	Hot-swappable, user replaceable batteries	
VOLTAGE REGULATION		
Voltage Regulation Description	Online, double-conversion power conditioning	
USER INTERFACE, ALERTS & CONTROLS		
Front Panel LCD Display	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, frequency, operating mode, alarm function and a variety of additional options	
Switches	RPO / ROO	
Alarm Cancel Operation	Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available	
Audible Alarm	Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions	
LED Indicators	4 status-indicating LEDs	
SURGE / NOISE SUPPRESSION		
UPS AC Suppression Joule Rating	190	
UPS AC Suppression Response Time	Instantaneous	
EMI / RFI AC Noise Suppression	Yes	
AC Suppression Joule Rating	190	
AC Suppression Response Time	Instantaneous	
PHYSICAL		
Primary Form Factor	Rackmount	
Rack Height	2U	
Cooling Method	Fan	
Included Mounting Accessory Description	Includes 4 post rackmount installation accessories	
Installation Form Factors Supported with Included Accessories	4 post 19 inch rackmount	
Installation Form Factors Supported with Optional Accessories	2 post rackmount (RK2PC)	
Minimum Required Rack Depth (cm)	52.58	
Minimum Required Rack Depth (inches)	20.7	
Optional Mounting Accessory Notes	2 post rail kit available, part # RK2PC	
Shipping Dimensions (hwd / in.)	9.45 x 21.66 x 23.63	





Shipping Weight (lbs.)	54.90	
11 3 3 4 7		
Shipping Weight (kg)	24.90	
UPS Housing Material	Metal	
Unit Dimensions (hwd / in.)	3.410 x 17.330 x 17.720	
Unit Weight (lbs.)	42.55	
Unit Weight (kg)	19.30	
ENVIRONMENTAL		
Operating Temperature Range	32° to 104°F (0° to 40°C)	
Storage Temperature Range	With battery: 32° to 104°F (0° to 40°C); without battery: -13° to 131°F (-25° to 55°C)	
Relative Humidity	0 to 96%, non-condensing	
AC Mode Efficiency Rating (100% Load)	90	
AC Economy Mode Efficiency Rating (100% Load)	95.8	
Online Mode Heat Dissipation (BTU/Hr) @ Full Load	512	
Battery Mode Heat Dissipation (BTU/Hr) @ Full Load	897	
Operating Elevation	0-10000 ft. (0-3000 m)	
Audible Noise	40 dB at 1m	
COMMUNICATIONS		
Network Management Cards	(1) WEBCARDLXE	
Network Monitoring Port Description	WEBCARDLXE Supports detailed monitoring of UPS and site power conditions; DB9 port supports RS232 and contact closure communications; not compatible with WEBCARDLX	
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert	
Communications Cable	USB and RS232 cable included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	
Network Management Card Description	Network management card optional	
Communications Interface	(1) Contact closure; (1) RS-232; (1) Slot for SNMP/Web interface; (1) USB	
Emergency Power Off (EPO)/Remote On-Off (ROO)	Yes	
LINE / BATTERY TRANSFER		
Transfer Time	0ms	
FEATURES & SPECIFICATIONS		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	





High Availability UPS Features	Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time
Green Energy-Saving Features	High efficiency economy mode operation; Individually controllable load banks
APPLICATIONS	
UPS Applications	Mission Critical Applications
STANDARDS & COMPLIANCE	
Product Certifications	UL 1778; cTUVus
Product Compliance	CE (Europe); FCC (USA); REACH; RoHS; Trade Agreements Act (TAA)
WARRANTY & SUPPORT	
Product Warranty Period (Worldwide)	2-year limited warranty
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance
Extended Service Plans	ADVANCED DEPOT EXCHANGEService Part Number: TL9SW5Y-1500UCParts, electronics and UPS batteries coverageNext business day shippingTechnical support5-year onsite plan: TLWFLN75XX-2509UCOnsite parts and labor coverage for 5 yearsParts, electronics and UPS batteries coverage24x7 onsite labor coverage, next-day responseNext-day shippingTechnical support

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark. All other trademarks are the property of their respective owners.