



SmartOnline 5000VA 4500W 120/208V Online Double-Conversion UPS with Stepdown Transformer - 18 5-20R, 2 L6-20R and 1 L6-30R Outlets, L6-30P Input, Network Card Included, Extended Run, 6U

MODEL NUMBER: SU5000RTF











Provides sine wave output, complete battery backup and power protection for mission-critical IT installations, edge networks and other advanced network applications.

Features

5kVA/4.5kW/208V Battery Backup for IT Installations and Edge Networks

This SmartOnline® rack-mount online double-conversion UPS system provides uninterrupted battery backup and AC power protection against blackouts, brownouts, surges and line noise that can damage valuable IT equipment or destroy data. An included stepdown transformer converts your UPS, utility or generator's 208V high-voltage input to 120V low-voltage output to allow connection of a wider range of components.

Expandable Internal Battery Backup Keeps You Operational Through Power Outages

The field-replaceable, hot-swappable valve regulated lead acid (VRLA) battery modules allow you to work through short power failures and give you enough time to safely save files and shut down your system in case of a prolonged blackout. Automatic restart after power outages reduces costly on-site visits. You can also connect up to four extended battery modules (BP180RT, sold separately) for hours of extended runtime.

Pre-Installed Network Interface Offers 24/7 Remote Access

The WEBCARDLXE network interface turns the SU5000RTF into a managed device on your network. It enables full remote configuration and SNMP-based UPS management, including load shedding, safe shutdowns and automated alerts. The IP-based Auto Probe feature ensures continuous network uptime by communicating with other network devices, detecting lost connectivity and automatically rebooting IT equipment without an on-site visit. Optional EnviroSense2 modules (E2MT, E2MTDO and E2MTHDI, all sold separately) provide a variety of environmental monitoring and control options.

NEMA Outlets Protect Your Connected Components

One L6-30R, two L6-20R and 18 5-20R managed outlets provide connected equipment with pure sine wave AC output and allow you to manage power consumption down to the outlet group level. Power provided by these outlets is filtered to protect connected equipment against damaging surges and line noise. The SU5000RTF also supports hardwired output.

Intuitive LCD Interface Keeps You Informed at a Glance

Highlights

- Protects equipment against blackouts, brownouts, transient surges and line noise
- Keeps equipment running during outages to allow time for file saves and safe shutdown
- Pre-installed WEBCARDLXE network card enables full remote access and control
- Stepdown transformer converts 208V input into 120V output for low-voltage equipment
- Optional extended battery modules allow extended runtime to keep equipment powered

Package Includes

- 5000VA 4500W 208V Double-Conversion UPS
- SUTFMR 120V stepdown transformer
- WEBCARDLXE network card
- USB cable
- RS-232 cable
- Tower support stands
- Cable gland for hardwire connection
- Rack-mounting hardware for UPS and transformer
- Quick start guide





The menu-driven LCD provides control settings and critical information to help diagnose any issues, including alarm and fault notifications. The interface rotates to accommodate both rack-mount and tower configurations, and it tilts up to 45 degrees for more comfortable viewing.

Advanced Communications Ports Allow for Automatic Saves and Shutdowns

RS-232 and USB ports connect to a serial-enabled device for a variety of communication options (cables are included). A dry-contact relay port can be programmed through the LCD to provide reliable communications to automation and industrial components. The RPO/ROO connectors permit emergency shutdown or remote restart of all connected equipment.

Versatile Installation Options

You can mount the SU5000RTF in just 6U of space in an EIA-standard 19-inch rack using the included 4-post rail kit or an optional 2-post rail kit (RK2PC, sold separately, one each required for each UPS, EBM or transformer). You can also adapt it for tower installation using the included support stands. The 10-foot power cord with NEMA L6-30P plug connects to a compatible AC outlet. A cable gland is included for alternate hardwire input.

Specifications

OVERVIEW		
UPC Code	037332286352	
UPS Type	On-Line	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	23.3A	
Nominal Input Voltage(s) Supported	200V AC; 208V AC; 220V AC; 230V AC; 240V AC	
Nominal Input Voltage Description	Factory configured to 208V	
UPS Input Connection Type	Hardwire; L6-30P	
Input Circuit Breakers	20A	
UPS Input Cord Length (ft.)	10	
UPS Input Cord Length (m)	3.1	
Recommended Electrical Service	30A	
Plug Type	L6-30P 10ft.	
Total Harmonic Distortion	< 2% THDV on linear load; < 5% THDV on non-linear load	
Input Cord Length (ft.)	10	
Input Cord Length (m)	3.05	
OUTPUT		
Output Capacity (VA)	5000	
Output Capacity (kVA)	5	
Output Capacity (Watts)	4500	
Output Capacity (kW)	4.5	





Power Factor	0.9	
Crest Factor	3:1	
Nominal Voltage Details	100V, 110V, 120V, 200V, 208V, 220V, 230V, 240V	
Frequency Compatibility	50 / 60 Hz	
Frequency Compatibility Details	50 or 60Hz, autosensing or configurable as a frequency converter	
Output Voltage Regulation (Line Mode)	+/- 1%	
Output Voltage Regulation (Battery Mode)	+/- 1%	
Output Receptacle Details	Hardwire output: 200-240V	
Output Circuit Breakers	20A breaker protects L6-20R and 5-20R outlets	
Output AC Waveform (AC Mode)	Pure Sine wave	
Output AC Waveform (Battery Mode)	Pure Sine wave	
Nominal Output Voltage(s) Supported	120V; 200V; 208V; 220V; 230V; 240V	
Output Receptacles	(18) 5-20R; Hardwire; (2) L6-20R; (1) L6-30R	
Individually Controllable Load Banks	No	
BATTERY		
Battery Type	Valve Regulated Lead Acid (VRLA)	
Runtime Full Load (min.)	3 min. (4500W)	
Runtime Half Load (min.)	11 min. (2250W)	
Expandable Runtime	Yes	
Expandable Runtime Description	Add up to 4 extended battery modules (EBM). Part number SP180RT	
External Battery Pack Compatibility	BP180RT	
DC System Voltage (VDC)	180	
Battery Access	Battery access door	
Internal UPS Replacement Battery Cartridge	744-A1974	
Battery Replacement Description	Hot-swappable, user replaceable batteries. UPS requires 1 Replacement Battery Cartridge.	
VOLTAGE REGULATION		
Voltage Regulation Description	Online, double-conversion power conditioning	
USER INTERFACE, ALERTS & CONTROLS		
Front Panel LCD Display	LCD graphical display	
Switches	RPO / ROO	





Alarm Cancel Operation	Press ESC to silence the alarm	
Audible Alarm	Audible alarm indicates utility failure, low-battery, overload, other UPS/Battery fault or remote shutdown conditions	
LED Indicators	4 status-indicating LEDs	
SURGE / NOISE SUPPRESSION		
UPS AC Suppression Response Time	0 ms	
EMI / RFI AC Noise Suppression	Yes	
PHYSICAL		
Primary Form Factor	Rackmount; Tower	
Rack Height	6U	
Cooling Method	Fan	
Included Mounting Accessory Description	Includes 4 post rackmount and tower pedestal accessories	
Installation Form Factors Supported with Included Accessories	4 post 19 inch rackmount; Tower	
Installation Form Factors Supported with Optional Accessories	2 post rackmount (RK2PC)	
Minimum Required Rack Depth (cm)	78.74	
Minimum Required Rack Depth (inches)	31	
Minimum Required Rack Depth with External Battery Pack (cm)	79	
Minimum Required Rack Depth with External Battery Pack (in.)	31	
Shipping Dimensions (hwd / in.)	30.00 x 38.00 x 28.50	
Shipping Weight (lbs.)	246.00	
UPS Housing Material	Metal	
UPS Power Module Weight (kg)	48.08	
UPS Power Module Weight (lbs.)	106	
Unit Dimensions (hwd / in.)	10.200 x 17.300 x 27.030	
Unit Weight (lbs.)	201.000	
Unit Weight (kg)	91.17	
ENVIRONMENTAL		
Operating Temperature Range	32° to 104°F (0° to 40°C)	
Relative Humidity	0-95% non-condensing	
AC Mode Efficiency Rating (100% Load)	93	
AC Economy Mode Efficiency Rating (100% Load)	98	





Online Mode Heat Dissipation (BTUHH) & Full Load 1560 1560 O-3280 ft. (0-1000 m) Audible Noise -45 dB at 1 meter COMMUNICATIONS Network Management Cards (1) & Special Cases "productLink" hind="/hiripplite eaton.com/Network-Card-Eaton-Tripp-Lite-Series-UPS-SystemsWEBCARDLXE"-wEBCARDLXE*-sas-Bhbsp. Network Monitoring Port Description USB and DB9 serial cables included monitoring of UPS and site power conditions; DB9 port supports RS232 and contact Colosure communications, not compatible with WEBCARDLX Tommunications Cable Network Management Card Network Management Card Network Management Card Network management card included Communications Interface (1) Contact closure; (1) Included network card; (1) RS-232; (1) USB Power (PPD)/Remails On-Off (ROO) Ves LINE / BATTERY TRANSFER Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Setpoint) 176V **FEATURES & SPECIFICATIONS** Cold-start operation supported During a Power Failure) Automatic Voltage Regulation (AVR): Expandable battery backup: Hot swappable batteries: On-Line/Double-Conversion; Pure sine wave output; Remote management: Surgenoise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation APPLICATIONS	Online Made Heat Dissination		
Operating Elevation 0-3280 ft. (0-1000 m) Audible Noise 45 dB at 1 meter COMMUNICATIONS Network Management Cards (1) .va.class="product.ink" href="//hripplite.eaton.com/Network-Card-Eaton-Tripp-Lite-Series-UPS-systems—WEBCARDLXE">WEBCARDLXE">WEBCARDLXE">WEBCARDLXE">WEBCARDLXE">WEBCARDLXE">WEBCARDLXE vivp-sa.nbsp. Network Monitoring Port Description WEBCARDLXE Supports detailed monitoring of UPS and site power conditions; DB9 port supports RS232 and contact closure communications; not compatible with WEBCARDLX PowerAlert Software For local monitoring via the UPS's bull-in-communication ports, download PowerAlert software at https://hitripplite.eaton.com/products/power-alert Communications Cable USB and DB9 serial cables included Network Management Card Network management card included Ocommunications Interface (1) Contact closure; (1) included network card; (1) RS-232; (1) USB Emergancy Power Off (EPO)/Remote On-Off (ROO) Yes LINE / BATTERY TRANSFER Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Setpoint) 276V FEATURES & SPECIFICATIONS Cold-start operation supported Cold Start (Startup in Battery Mode During a Power Failure) Cold-start operation supported High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries: On-Line/Double-Conversion, Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation		1150	
Audible Noise	Battery Mode Heat Dissipation (BTU/Hr) @ Full Load	1560	
Network Management Cards (1) . <a (0="" (1)="" (avr);="" (epo)="" (roo)="" (setpoint)="" (startup="" -webcardlxe"-a-="" 176v="" a="" and="" at="" automatic="" backup;="" batteries;="" battery="" built-in="" cable="" cables="" card="" card;="" class="productLink" closure="" closure;="" cold-start="" communication="" communications="" communications;="" compatible="" conditions;="" contact="" db9="" description="" detailed="" double-conversion="" double-conversion;="" download="" during="" economy="" efficiency="" emergency="" energy-saving="" expandable="" failure)="" features="" for="" green="" high="" hot="" href="/tripplite eaton.com/Network-Card-Eaton-Tripp-Lite-Series-UPS-Systems-WEBCARDLXE" https:="" in="" included="" interface="" line="" local="" low="" management="" management;="" mode="" monitoring="" ms.)="" network="" no="" noise="" not="" of="" off="" on-line="" on-off="" online,="" operation<="" output;="" port="" ports,="" power="" power-alert="" poweralert="" productlink"="" products="" protection;="" pure="" regulation="" remote="" rs-232;="" rs232="" serial="" sine="" site="" software="" supports="" surge="" swappable="" td="" the="" time="" to="" transfer="" tripplite.eaton.com="" ups="" ups's="" usb="" ves="" via="" voltage="" wave="" webcardlx="" webcardlxe="" with="" zero=""><td>Audible Noise</td><td><45 dB at 1 meter</td>	Audible Noise	<45 dB at 1 meter	
Systems-WEBCARDLXE-Yas-Anbsp; Network Monitoring Port Description WEBCARDLXE Supports detailed monitoring of UPS and site power conditions; DB9 port supports RS232 and contact closure communications; not compatible with WEBCARDLX PowerAlert Software For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert Communications Cable USB and DB9 serial cables included Network Management Card Network management card included Communications Interface (1) Contact closure; (1) Included network card; (1) RS-232; (1) USB Emergency Power Off (EPO)/Remote On-Off (ROO) Ves LINE / BATTERY TRANSFER Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Selpoint) 176V FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion, Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation			
contact closure communications; not compatible with WEBCARDLX PowerAlert Software For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert Communications Cable USB and DB9 serial cables included Network Management Card Description Network management card included Communications Interface (1) Contact closure; (1) Included network card; (1) RS-232; (1) USB Emergency Power Off (EPO)/Remote On-Off (ROO) LINE / BATTERY TRANSFER Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Setpoint) High Voltage Transfer to Battery Power (Setpoint) 276V FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) Automatic Voltage Regulation (AVR): Expandable battery backup: Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation	Network Management Cards	(1) WEBCARDLXE	
https://tripplite.eaton.com/products/power-alert Communications Cable USB and DB9 serial cables included Network Management Card Description (1) Contact closure; (1) Included network card; (1) RS-232; (1) USB Emergency Power Off (EPO)/Remote On-Off (ROO) LINE / BATTERY TRANSFER Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Setpoint) 176V FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time High efficiency economy mode operation	Network Monitoring Port Description	WEBCARDLXE Supports detailed monitoring of UPS and site power conditions; DB9 port supports RS232 and contact closure communications; not compatible with WEBCARDLX	
Network Management Card Description Network Management Card Description Network management card included Communications Interface (1) Contact closure; (1) Included network card; (1) RS-232; (1) USB Emergency Power Off (EPO)/Remote On-Off (ROO) Yes LINE / BATTERY TRANSFER Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Setpoint) 176V High Voltage Transfer to Battery Power (Setpoint) 276V FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation	PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert	
Description Communications Interface (1) Contact closure; (1) Included network card; (1) RS-232; (1) USB Emergency Power Off (EPO)/Remote On-Off (ROO) Yes LINE / BATTERY TRANSFER Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Setpoint) 176V High Voltage Transfer to Battery Power (Setpoint) FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) Cold-start operation supported High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation	Communications Cable	USB and DB9 serial cables included	
Emergency Power Off (EPO)/Remote On-Off (ROO) Ves LINE / BATTERY TRANSFER Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Setpoint) High Voltage Transfer to Battery Power (Setpoint) 276V FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation	Network Management Card Description	Network management card included	
LINE / BATTERY TRANSFER Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Setpoint) 176V High Voltage Transfer to Battery Power (Setpoint) 276V FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) Cold-start operation supported High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation	Communications Interface	(1) Contact closure; (1) Included network card; (1) RS-232; (1) USB	
Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Setpoint) 176V High Voltage Transfer to Battery Power (Setpoint) 276V FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) Cold-start operation supported High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation	Emergency Power Off (EPO)/Remote On-Off (ROO)	Yes	
Transfer Time No transfer time (0 ms.) in online, double-conversion mode Low Voltage Transfer to Battery Power (Setpoint) 176V High Voltage Transfer to Battery Power (Setpoint) 276V FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) Cold-start operation supported High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation	LINE / DATTERY TRANSFER		
Low Voltage Transfer to Battery Power (Setpoint) High Voltage Transfer to Battery Power (Setpoint) 276V FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) Cold-start operation supported High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation		No transfer time (O ma) in paline, double appropriate mode	
High Voltage Transfer to Battery Power (Setpoint) FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) Cold-start operation supported High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation	Low Voltage Transfer to Battery		
FEATURES & SPECIFICATIONS Cold Start (Startup in Battery Mode During a Power Failure) Cold-start operation supported High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation	High Voltage Transfer to Battery	276V	
During a Power Failure) High Availability UPS Features Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation			
Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time Green Energy-Saving Features High efficiency economy mode operation	Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
	High Availability UPS Features	Automatic Voltage Regulation (AVR); Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Pure sine wave output; Remote management; Surge/noise protection; Zero transfer time	
APPLICATIONS	Green Energy-Saving Features	High efficiency economy mode operation	
	APPLICATIONS		
UPS Applications Mission Critical Applications	UPS Applications	Mission Critical Applications	
STANDARDS & COMPLIANCE			
Product Certifications NOM (Mexico); cUL Listed; EN 62040-2	Product Certifications	NOM (Mexico); cUL Listed; EN 62040-2	
Product Compliance FCC Part 15 Class A (USA); CE (Europe); FCC (USA); ENERGY STAR Qualified; RoHS	Product Compliance	FCC Part 15 Class A (USA); CE (Europe); FCC (USA); ENERGY STAR Qualified; RoHS	
WARRANTY & SUPPORT			
Product Warranty Period (U.S. & 2-year limited warranty		2-year limited warranty	





Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance
Extended Service Plans	5-year depot exchange plan: TL9SW5Y-6000UCExpedited parts coverage for 5 yearsParts, electronics, and UPS battery coverageNext business day shippingTechnical support5-year onsite plan: TLWFLN75XX-6009UCOnsite parts and labor coverage for 5 yearsParts, electronics, and UPS battery coverage24x7 onsite labor coverage, next-day responseNext-day shippingTechnical supportStartup 24x7: TLSU05NXXX-6009UC Assembly 24x7: TLAS00NXXX-6009UC Onsite preventative maintenance 24x7: TL0005NXXX-6009UC

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2024 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.