PDU3EVSR10L2130

3-Phase Switched 0U Vertical PDU





200/208/240V NEMA L21-30P 200/208/240V



Single-Phase

Output





30 Outlets



10kW Load

Capacity



device.

Touchscreen H



HTML5 0U Network Rack Mount Interface




Toolless Mounting Buttons


- 3-Phase Input Plug

 A Color Touchscreen LCD
- B C13 and C19 Outlets with Multi-Function LEDs
- 20A 2-Pole Hydraulic Magnetic Circuit Breakers
- C13 and C19 Plug-Lock Inserts
- Removable Mounting
 Brackets
- F Toolless Mounting
 Buttons with Removable
 90° Rotation Brackets
- G 10 ft. Input Power Cord
- NEMA L21-30P Input Plug
- I LX Platform Interface
- USB-B Port (for Direct Console Access)
- K USB-A Ports (for EnviroSense2 Sensors)
- **■** RJ45 Configuration Port
- M Ethernet Port











Color Touchscreen LCD: Easily toggle between menus to monitor input current level per phase, output current per load bank and per outlet, environmental sensor data and network information. It also generates a unique QR code to allow access to the switchable PDU through a mobile








Standard

Note: Installed 17.67 mm toolless mounting buttons can be replaced with included 14.17 mm buttons for additional compatibility.




*Add optional EnviroSense2 (E2) modules for temperature/humidity monitoring and dry contact interface.

Specifications

Unit Weight

Standards



FCC Class A; RoHS; TAA

Tested to UL 60950-1 (US & Canada), NOM (Mexico),

20 lb. / 9 kg

• Distributes power to 30 outlets (8 C13 & 2 C19 per bank)

- Java-free, HTML5-based network interface allows for remote monitoring and control via SNMP, Web, SSH or telnet
- Reports current for each bank, phase and total output in real time with 1% billing grade accuracy
- Perfect for rack-mount server, network and telecom applications

SEE NEXT PAGE FOR DETAILED UNIT MEASUREMENTS



1111 W. 35th Street Chicago, IL 60609 USA 773.869.1234 www.tripplite.com

