



SM3000RML2UTAA Estimated Runtime

Load in Watts

UPS	Battery Pack	400W	600W	800W	1000W	1200W	1400W	1600W	1800W	2000W	2200W	2400W	2600W	2800W	2880W
SM3000RML2UTAA	Included Batteries	48	29	20	15	12	10.2	8.0	6.7	5.7	4.9	4.3	3.8	3.2	3.0
SM3000RML2UTAA	1 BP48V242UTAA	182	115	82	63	50	42	35	30	26	23	20	18	16	16
SM3000RML2UTAA	1 BP48V60RT3UTAA	387	252	183	142	114	95	80	69	60	53	47	42	38	37
SM3000RML2UTAA	2 BP48V60RT3UTAA	642	425	313	245	200	167	142	122	107	95	85	76	70	67
SM3000RML2UTAA	3 BP48V60RT3UTAA	894	598	444	350	287	242	206	178	156	139	125	113	103	99
SM3000RML2UTAA	4 BP48V60RT3UTAA	1142	771	576	456	376	318	271	235	207	185	166	151	137	133
SM3000RML2UTAA	5 BP48V60RT3UTAA	1386	942	707	562	464	394	337	293	259	231	208	189	173	167
SM3000RML2UTAA	6 BP48V60RT3UTAA	1626	1110	837	668	553	470	404	352	311	278	251	228	209	202
SM3000RML2UTAA	7 BP48V60RT3UTAA	1862	1277	966	773	641	546	470	410	363	325	294	267	245	238
SM3000RML2UTAA	8 BP48V60RT3UTAA	2093	1442	1094	877	729	622	536	469	416	372	337	307	282	273
SM3000RML2UTAA	9 BP48V60RT3UTAA	2320	1605	1221	981	817	698	602	527	468	420	380	347	318	309
SM3000RML2UTAA	10 BP48V60RT3UTAA	2543	1766	1347	1084	904	774	668	586	520	467	423	387	378	370

All runtime values are in minutes.