



SMX3000XLRT2U Estimated Runtime

Load in Watts

UPS	Battery Pack	500W	1,000W	1,100W	1,200W	1,300W	1,400W	1,500W	1,600W	1,700W	1,800W	1,900W	2,000W	2,200W	2,240W
SMX3000XLRT2U	Internal Batteries	30	12	11	9.7	8.7	7.8	7.1	6.4	5.9	5.4	5.0	4.6	4.1	4.0
SMX3000XLRT2U	1 BP48V24-2U	105	46	40	36	33	30	27	25						
SMX3000XLRT2U	1 BP48V60RT3U	212	96	85	77	69	63	58	53						
SMX3000XLRT2U	2 BP48V60RT-3U	424	200	179	161	147	134	124	115						
SMX3000XLRT2U	3 BP48V60RT-3U	637	308	277	251	229	210	194	180						
SMX3000XLRT2U	4 BP48V60RT-3U	849	417	376	341	312	287	265	247						
SMX3000XLRT2U	5 BP48V60RT-3U	1,057	526	475	432	396	365	338	314						
SMX3000XLRT2U	6 BP48V60RT-3U	1,263	635	574	523	480	443	411	383						
SMX3000XLRT2U	7 BP48V60RT-3U	1,465	743	673	614	564	521	484	451						
SMX3000XLRT2U	8 BP48V60RT-3U	1,665	851	772	705	648	599	556	519						
SMX3000XLRT2U	9 BP48V60RT-3U	1,862	958	870	795	731	676	629	587						
SMX3000XLRT2U	10 BP48V60RT-3U	2,055	1,065	967	884	814	754	701	655						

All runtime values are in minutes.