



## SU16KRTAA Estimated Runtime

UPS	Battery Pack	Battery Pack Qty	Load in Watts													
			1,000	2,000	3,000	4,000	5,000	6,000	7,000	8,000	9,000	10,000	11,000	12,000	13,000	14,000
SU16KRTAA	Included Batteries	0	165	76	46	32	23	18	14	12	10	8.9	7.8	7.0	6.3	5.7
SU16KRTAA	BP240V10RT3UTAA	2	372	184	118	84	65	52	43	36	31	27	24	21	19	17
SU16KRTAA	BP240V10RT3UTAA	4	577	293	190	138	106	86	71	60	52	46	40	36	33	30
SU16KRTAA	BP240V10RT3UTAA	6	780	404	264	193	150	121	101	86	74	65	58	52	47	43
SU16KRTAA	BP240V10RT3UTAA	8	982	514	340	249	195	158	133	113	98	86	77	69	62	57
SU16KRTAA	BP240V10RT3UTAA	10	1181	624	415	307	240	196	164	141	122	108	96	86	78	71
SU16KRTAA	BP240V10RT3UTAA	12	1376	734	491	364	286	234	197	169	147	129	115	104	94	86
SU16KRTAA	BP240V10RT3UTAA	14	1570	843	566	421	332	273	230	197	172	152	136	122	111	101
SU16KRTAA	BP240V10RT3UTAA	16	1760	951	642	479	379	311	263	226	197	174	156	141	128	117
SU16KRTAA	BP240V10RT3UTAA	18	1947	1059	717	536	425	350	296	255	223	197	176	159	145	133
SU16KRTAA	BP240V10RT3UTAA	20	2132	1166	792	594	471	389	329	284	248	220	197	178	162	149
SU16KRTAA	BP240V787C-1PH	2	1697	915	617	460	363	298	252	216	189	167	149	134	122	112
SU16KRTAA	BP240V787C-1PH	4	3243	1823	1257	953	764	634	541	469	412	367	330	300	274	252

All runtime values are shown in minutes.